

## Quick guide to configuring MyReserve 25 via web interface/Web UI:

**Note:** Alternatively, you can carry out the configuration via the MyReserve App [FaQ MyReserve App](#).

To connect to MyReserve via LAN, the storage and the computer must be on the same network.

1. search the customer network for the device name/host name <http://mrc.local/>
  - a. If the device name/host name is not displayed in the network, you can also use MyReserve APP to read the IP address under the "Pro" options in the "Device Settings"
  - b. The MyReserve can also be identified using the MAC address.  
Example: Serial number: **0004A30B000C49BA** -> MAC address: **00:04:A3:0C:49:BA**
2. enter <http://mrc.local/> or the corresponding IP address in the address bar of your browser

The screenshot displays the MyReserve Command web interface. It is divided into several sections:

- Status values:** A table showing the status of various components with corresponding indicator lights and hex values.

BMS Status:	<span style="color: green;">●</span>	0x0
Sys Status:	<span style="color: blue;">●</span>	0x102000
Com Status:	<span style="color: green;">●</span>	0x0
Internet Status:	<span style="color: green;">●</span>	0x0
- Performance values:** A table showing performance metrics.

SoC:	93	%
PBat:	0	W
PPV:	3889	W
PGrid:	-3750	W
- Network configuration:** A form for setting network parameters.

MAC address:	00:04:A3:0C:49:BA
DHCP:	<input checked="" type="checkbox"/>
IP address:	192.168.202.180
Netmask:	255.255.252.0
Gateway:	192.168.200.1
Hostname:	MRC 3
- Country code:** A dropdown menu set to "DE (Germany)" with a "Submit" button below it.

At the bottom, there is a green status message: "Connection to Command ok 3.12.2020, 13:27:20". The footer contains copyright information for SOLARWATT GmbH and links for "Imprint", "Terms of Use", and "Privacy Policy".

- Under "Country code" you can change the country setting
- Under "Hostname" you can assign a number from 1 to 99 for better network identification in case there are more than one MyReserve 25 (cluster) in the network.

**Note:** confirm each setting by clicking on the respective "Submit" button.